

**Contents of box:**

Connector PCB



Colour may vary. Fits MixRack ESA. MixRack ESB.

Auvitran PCB




Check the Type is correct:

**MixRack** Fits MixRack ESA & ESB.

**Surface** Do not use. Return to supplier.


**Tools required:**

Torx T10 

Allen & Heath module extractor  
Supplied with MixRack.



**1. Remove Remote Audio Module.**



**2. Remove XLR screws including ESA / blanks / DARS where fitted.**


**3. Remove PCB screws x8.**



If ESA is fitted, remove the PAFL knob, push the shaft in and slide the PCB sideways to free the locking tabs


**4. Push fit Connector PCB.**

Fit all XLR screws including ESA / blanks / DARS where fitted.



**5. Replace PCB and 8x PCB screws.**

**6. Push fit Auvitran PCB.**



**7. The Remote Audio Module can now be replaced. Check all screws.**