

Every voice, instrument, system and room is slightly different, but with a known microphone and mixer, it's still possible to get a head start and speed up your setup using presets.

These EQ presets for the Qu series have been created by professionals to give you the best possible starting point when using Audio Technica microphones on a variety of sources.

File Name	Preset Name	Microphone	Source
LIB000.DAT	ATM250KI	ATM250	Kick Drum
LIB001.DAT	PRO25KI	PRO25ax	Kick Drum
LIB002.DAT	MB6KKI	MB6k	Kick Drum
LIB003.DAT	ATM650SN	ATM650	Snare Drum
LIB004.DAT	ATM350SN	ATM350	Snare Drum
LIB005.DAT	MB5KSN	MB5k	Snare Drum
LIB006.DAT	ATM450HH	ATM450	Hi Hats
LIB007.DAT	PRO37HH	PRO37	Hi Hats
LIB008.DAT	AT2031HH	AT2031	Hi Hats
LIB009.DAT	MB2KHH	MB2k	Hi Hats
LIB010.DAT	ATM350TT	ATM350	Toms
LIB011.DAT	ATM230TT	ATM230	Toms
LIB012.DAT	PRO25TT	PRO25ax	Toms
LIB013.DAT	MB5KTT	MB5k	Toms
LIB014.DAT	ATM650EG	ATM650	Electric Guitar
LIB015.DAT	MB2KEG	MB2k	Electric Guitar
LIB016.DAT	AT2031AG	AT2031	Acoustic Guitar
LIB017.DAT	ATM450AG	ATM450	Acoustic Guitar
LIB018.DAT	PRO37AG	PRO37	Acoustic Guitar
LIB019.DAT	MB4KAG	MB4k	Acoustic Guitar
LIB020.DAT	ATM510VO	ATM510	Vocal
LIB021.DAT	ATM710VO	ATM710	Vocal
LIB022.DAT	PRO61VO	PRO61	Vocal
LIB023.DAT	AT2010VO	AT2010	Vocal
LIB024.DAT	MB1KVO	MB1k	Vocal
LIB025.DAT	MB3KVO	MB3k	Vocal
LIB026.DAT	ATM350BR	ATM350	Brass

## Transferring the presets to the Qu

1. Format a USB drive (an external HDD/SSD or Stick/Key) using the Qu by connecting it to the Qu-Drive port, going to the **Setup > Utility > Qu-Drive** screen and touching the **Format** button. This will setup the device for use as a Qu-Drive.

**Note:** If you already use a USB drive as a Qu-Drive for audio/data then you may not need to reformat it, but as these Library files are numbered from '000' be aware you will overwrite any Libraries you've stored on the drive in the past.

2. Remove the USB drive from the Qu and connect it to your computer.
3. Copy all library (\*.DAT) files from the **LIBRARY** folder in the ProFactory Mic Preset package you've downloaded to the **[USB]AHQU\LIBRARY** folder on the USB drive (you can choose which presets you transfer to the Qu later).
4. Eject the drive then connect it to the Qu again.
5. Go to the **Setup > USB Data > Libraries** screen.
6. Copy each Library item you want from the USB drive to the Qu.
  - i. Touch a preset on the right from the **USB Libraries** list.
  - ii. Touch the **◀ to Qu** button in the centre.

**Note:** All presets copied over to the Qu will be included when storing a show.

## Recalling a preset

1. Go to the **Processing** screen and select the channel where you want to use the preset.
2. Go to the **PEQ** section for that channel.
3. On a Qu-16, Qu-24, Qu-32 or Qu-Pac, press the **Fn** key (labelled **Library**) to open the PEQ and Channel Library.  
On a Qu-SB, or if using Qu-Pad with any Qu model, touch the **Library** button on the left hand side.
4. On Qu-16, Qu-24, Qu-32 or Qu-Pac, touch the **User** button on the left to show User Libraries.
5. Select the preset you wish to use from the User PEQ Library.
6. Touch the **Recall** button.

If needed, you can now tweak the PEQ and even store your own version of the preset for future use.

**Note:** Some presets are flat when recalled, though you'll notice frequencies have been adjusted to best suit the microphone and source, meaning you may only need to tweak the PEQ gain controls in the first instance.