

Every voice, instrument, system and room is slightly different, but with a known microphone and mixer, it's still possible to get a head start and speed up your setup using presets.

These EQ presets for the Qu series have been created by professionals to give you the best possible starting point when using sE Electronics microphones on a variety of sources.

File Name	Preset Name	Microphone	Source
LIB000.DAT	4400_GTR	4400a	Guitar
LIB001.DAT	4400_SAX	4400a	Saxophone
LIB002.DAT	4400_VLN	4400a	Violin
LIB003.DAT	4400a_OH	4400a	Drums Overhead
LIB004.DAT	4400a_PN	4400a	Piano
LIB005.DAT	4400a_TT	4400a	Toms
LIB006.DAT	RN17_OH	RN17	Drums Overhead
LIB007.DAT	RN17_PNO	RN17	Piano
LIB008.DAT	RN17_VLN	RN17	Violin
LIB009.DAT	RN17_akk	RN17	Acoustic Guitar
LIB010.DAT	RNR1_GTR	RNR1	Electric Guitar
LIB011.DAT	RNR1_OH	RNR1	Drums Overhead
LIB012.DAT	RNR1_PNO	RNR1	Piano
LIB013.DAT	RNR1_SAX	RNR1	Saxophone
LIB014.DAT	RNR1_VLN	RNR1	Violin
LIB015.DAT	sE8_OH	RNR1	Drums Overhead
LIB016.DAT	sE8_PNO	sE8	Piano
LIB017.DAT	sEV3_SN	sE8	Snare
LIB018.DAT	sEV3_VOX	V3	Vocal
LIB019.DAT	sEV7_GTR	V3	Electric Guitar
LIB020.DAT	sEV7_SN	V7	Snare
LIB021.DAT	sEV7_VOX	V7	Vocal
LIB022.DAT	sEVR_GTR	VR	Electric Guitar
LIB023.DAT	sEVR_OH	VR	Drums Overhead
LIB024.DAT	sEVR_PNO	VR	Piano
LIB025.DAT	sEVR_SAX	VR	Saxophone
LIB026.DAT	sEVR_VLN	VR	Violin
LIB027.DAT	X1A_PNO	VR	Piano
LIB028.DAT	X1A_VLN	X1A	Violin
LIB029.DAT	X1A_akkG	X1A	Acoustic Guitar
LIB028.DAT	X1D_Kick	X1D	Kickdrum
LIB031.DAT	X1R_PNO	X1D	Piano
LIB032.DAT	X1R_VLN	X1A	Violin
LIB033.DAT	X1R_akkG	X1A	Acoustic Guitar

Transferring the presets to the Qu

1. Format a USB drive (an external HDD/SSD or Stick/Key) using the Qu by connecting it to the Qu-Drive port, going to the **Setup > Utility > Qu-Drive** screen and touching the **Format** button. This will setup the device for use as a Qu-Drive.

Note: If you already use a USB drive as a Qu-Drive for audio/data then you may not need to reformat it, but as these Library files are numbered from '000' be aware you will overwrite any Libraries you've stored on the drive in the past.

2. Remove the USB drive from the Qu and connect it to your computer.
3. Copy all library (*.DAT) files from the **LIBRARY** folder in the ProFactory Mic Preset package you've downloaded to the **[USB]AHQU\LIBRARY** folder on the USB drive (you can choose which presets you transfer to the Qu later).
4. Eject the drive then connect it to the Qu again.
5. Go to the **Setup > USB Data > Libraries** screen.
6. Copy each Library item you want from the USB drive to the Qu.
 - i. Touch a preset on the right from the **USB Libraries** list.
 - ii. Touch the **◀ to Qu** button in the centre.

Note: All presets copied over to the Qu will be included when storing a show.

Recalling a preset

1. Go to the **Processing** screen and select the channel where you want to use the preset.
2. Go to the **PEQ** section for that channel.
3. On a Qu-16, Qu-24, Qu-32 or Qu-Pac, press the **Fn** key (labelled **Library**) to open the PEQ and Channel Library.
On a Qu-SB, or if using Qu-Pad with any Qu model, touch the **Library** button on the left hand side.
4. On Qu-16, Qu-24, Qu-32 or Qu-Pac, touch the **User** button on the left to show User Libraries.
5. Select the preset you wish to use from the User PEQ Library.
6. Touch the **Recall** button.

If needed, you can now tweak the PEQ and even store your own version of the preset for future use.

Note: Some presets are flat when recalled, though you'll notice frequencies have been adjusted to best suit the microphone and source, meaning you may only need to tweak the PEQ gain controls in the first instance.