

V_C20M1_LF1
C20M1_LF1

C20M1_LF1

D_C20M1_LF1
C20M1_LF1

C20M1_LF1



ALLEN & HEATH

Alford Industrial Estate,

Penny, Cornwall

England TR24 5LJ

Tel: +44 (0)1524 372330

Fax: +44 (0)1524 371153


ISSUE NO.	DATE	BY
1	200703	...
2	200712	...
3	200802	...

REV.	DATE	DESCRIPTION
1	200703	...
2	200712	...
3	200802	...


TITLE: XB-14 MK2 MIX
PAGE:
DRG No: C8395
ISSUE: 1
SHEET: 0 OF 2

31







AUDITION OUT



EXT MON IN



GUEST PHONES 1



ALLEN & HEATH


ALLEN & HEATH
Parsippany, Connecticut 06866
England, Telford, Shropshire

Tel: +44 (0)1535 372930
Fax: +44 (0)1535 376153

REV	DATE	BY	CHK
001	08/07/02	AL	AL
002	08/07/02	AL	AL
003	08/07/02	AL	AL
004	08/07/02	AL	AL



FILE: 0806_107_004



PRINTED: 08/07/02 09:00:00

TITLE: XB-14 MK2 MIX
PAGE:
All parts to be Bufile Compliant
DRG No: C8395 ISSUE: 1 SHEET: 1 OF 2

Designator	Description	A&H PART
C1	CAPACITOR CERAMIC SMD0805 10N 50V (AF2849)	AF2849
C2	CAPACITOR CERAMIC SMD0805 10N 50V (AF2849)	AF2849
C3	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C4	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C5	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C6	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C8	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C9	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C11	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C12	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C14	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C15	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C17	CAPACITOR ELECTROLYTIC 47uF 63V (AF0217)	AF0217
C18	CAPACITOR ELECTROLYTIC 47uF 25V (AF0208)	AF0208
C19	CAPACITOR ELECTROLYTIC 47uF 25V (AF0208)	AF0208
C20	CAPACITOR ELECTROLYTIC 47uF 25V (AF0208)	AF0208
C21	CAPACITOR ELECTROLYTIC 47uF 25V (AF0208)	AF0208
C22	CAPACITOR ELECTROLYTIC 330uF 25V (AF0227)	AF0227
C23	CAPACITOR ELECTROLYTIC 330uF 25V (AF0227)	AF0227
C24	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C25	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C26	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C27	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C28	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C29	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C30	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C31	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C32	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C33	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C34	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C35	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C36	CAPACITOR CERAMIC SMD0805 33P (AF4887)	AF4887
C37	CAPACITOR ELECTROLYTIC 47uF 25V (AF0208)	AF0208
C38	CAPACITOR ELECTROLYTIC 47uF 25V (AF0208)	AF0208
C40	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C41	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C42	CAPACITOR CERAMIC SMD0805 100N 50V (AF2851)	AF2851
C75	CAPACITOR CERAMIC SMD0805 22P (AF2992)	AF2992
C76	CAPACITOR CERAMIC SMD0805 22P (AF2992)	AF2992
C77	CAPACITOR CERAMIC SMD0805 22P (AF2992)	AF2992
C78	CAPACITOR CERAMIC SMD0805 22P (AF2992)	AF2992
C79	CAPACITOR CERAMIC SMD0805 22P (AF2992)	AF2992
C80	CAPACITOR CERAMIC SMD0805 22P (AF2992)	AF2992
C81	CAPACITOR CERAMIC SMD0805 22P (AF2992)	AF2992
C82	CAPACITOR CERAMIC SMD0805 22P (AF2992)	AF2992
C83	CAPACITOR ELECTROLYTIC 47uF 25V (AF0208)	AF0208
C84	CAPACITOR ELECTROLYTIC 47uF 25V (AF0208)	AF0208
CN1	RCA PHONO DUAL HORIZONTAL W/R (YKC21-3120 (PS3120)) (AL6830)	AL6830

CN2	RCA PHONO DUAL HORIZONTAL W/R (YKC21-3120 (PS3120)) (AL6830)	AL6830
CN3	JACK SOCKET HORIZONTAL 6 PIN HEADPHONE(loco (AL6893)	AL6893
CN4	Connector IDC,Molex Type 0.1" Pitch 17x2 pins (AL4345)	AL4345
CN5	Connector IDC,Molex Type 0.1" Pitch 10x2 pins (AL4336)	AL4336
CN7	SIL 5 M STRT LCK (AL4594)	AL4594
CN16	Connector IDC,Molex Type 0.1" Pitch SIL 3 pins (AL0320)	AL0320
CN17	Connector IDC,Molex Type 0.1" Pitch SIL 3 pins (AL0320)	AL0320
JP7	JUMP 2 OPTION JUMPER (AL0334)	AL0334
JP8	JUMP 2 OPTION JUMPER (AL0334)	AL0334
LD1	LED T1 3mm RED (AE0086)	AE0086
Q1	TRANSISTOR NPN BC848B (AE3332)	AE3332
Q2	TRANSISTOR NPN BC848B (AE3332)	AE3332
Q3	TRANSISTOR PNP BC858B (AE3042)	AE3042
Q4	TRANSISTOR PNP BC858B (AE3042)	AE3042
Q5	TRANSISTOR NPN BC848B (AE3332)	AE3332
Q6	TRANSISTOR PNP BC858B (AE3042)	AE3042
Q7	TRANSISTOR NPN BC848B (AE3332)	AE3332
Q8	TRANSISTOR PNP BC858B (AE3042)	AE3042
R1	RESISTOR CARBON SMD0805 0R0 5% (AC2838)	AC2838
R2	RESISTOR CARBON SMD0805 0R0 5% (AC2838)	AC2838
R3	RESISTOR CARBON SMD0805 0R0 5% (AC2838)	AC2838
R4	RESISTOR CARBON SMD0805 100R 5% (AC3026)	AC3026
R5	RESISTOR CARBON SMD0805 100R 5% (AC3026)	AC3026
R6	RESISTOR METAL FILM SMD0805 330R 1% (AC3056)	AC3056
R7	RESISTOR METAL FILM SMD0805 330R 1% (AC3056)	AC3056
R8	RESISTOR METAL FILM SMD0805 33K 1% (AC3532)	AC3532
R9	RESISTOR METAL FILM SMD0805 33K 1% (AC3532)	AC3532
R10	RESISTOR CARBON SMD0805 47K 5% (AC3035)	AC3035
R11	RESISTOR CARBON SMD0805 47K 5% (AC3035)	AC3035
R12	RESISTOR CARBON SMD0805 47K 5% (AC3035)	AC3035
R13	RESISTOR CARBON SMD0805 47K 5% (AC3035)	AC3035
R18	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R19	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R20	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R21	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R24	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R25	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R27	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R28	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R31	RES SMD 15K 1% 0805 METAL FILM AC5050	AC5050
R32	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R33	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R35	RES SMD TF 47R 0.5% 0805 MET (H1Y82LL) (AC6009)	AC6009
R36	RESISTOR METAL FILM SMD0805 4K7 1% (AC3062)	AC3062
R37	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R38	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R39	RESISTOR CARBON 10R PRE FORMED RADIAL 1/4W 5% (AC5077)	AC5077
R40	RESISTOR METAL FILM SMD0805 75R 1% (AC5416)	AC5416

R41	RESISTOR METAL FILM SMD0805 22K 1% (AC2842)	AC2842
R43	RESISTOR METAL FILM SMD0805 22K 1% (AC2842)	AC2842
R45	RESISTOR METAL FILM SMD0805 22K 1% (AC2842)	AC2842
R48	RESISTOR CARBON SMD0805 5K6 5% (AC4106)	AC4106
R50	RESISTOR CARBON SMD0805 5K6 5% (AC4106)	AC4106
R54	RESISTOR SMD NOT FITTED 0805	NO PART
R55	RESISTOR CARBON SMD0805 68R 5% (AC4101)	AC4101
R56	RESISTOR CARBON SMD0805 68R 5% (AC4101)	AC4101
R57	RESISTOR CARBON 10R PRE FORMED RADIAL 1/4W 5% (AC5077)	AC5077
R58	RESISTOR CARBON 10R PRE FORMED RADIAL 1/4W 5% (AC5077)	AC5077
R59	RESISTOR CARBON 10R PRE FORMED RADIAL 1/4W 5% (AC5077)	AC5077
R60	RESISTOR METAL FILM SMD0805 75R 1% (AC5416)	AC5416
R63	RESISTOR CARBON SMD0805 100R 5% (AC3026)	AC3026
R64	RESISTOR METAL FILM SMD0805 330R 1% (AC3056)	AC3056
R65	RESISTOR METAL FILM SMD0805 33K 1% (AC3532)	AC3532
R66	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R67	RESISTOR CARBON SMD0805 47K 5% (AC3035)	AC3035
R68	RESISTOR CARBON SMD0805 100R 5% (AC3026)	AC3026
R69	RESISTOR METAL FILM SMD0805 330R 1% (AC3056)	AC3056
R70	RESISTOR METAL FILM SMD0805 33K 1% (AC3532)	AC3532
R71	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R72	RESISTOR CARBON SMD0805 47K 5% (AC3035)	AC3035
R75	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R76	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R77	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R78	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R79	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R80	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R81	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R82	RESISTOR METAL SMD0805 8K2 1% (AC5017)	AC5017
R83	RESISTOR METAL FILM SMD0805 4K7 1% (AC3062)	AC3062
R84	RESISTOR METAL FILM SMD0805 4K7 1% (AC3062)	AC3062
R85	RESISTOR METAL FILM SMD0805 4K7 1% (AC3062)	AC3062
R86	RESISTOR METAL FILM SMD0805 4K7 1% (AC3062)	AC3062
R87	RESISTOR METAL FILM SMD0805 4K7 1% (AC3062)	AC3062
R88	RESISTOR METAL FILM SMD0805 4K7 1% (AC3062)	AC3062
R89	RESISTOR METAL FILM SMD0805 4K7 1% (AC3062)	AC3062
R90	RESISTOR METAL FILM SMD0805 4K7 1% (AC3062)	AC3062
R91	RESISTOR CARBON SMD0805 47R 5% (AC3036)	AC3036
R92	RESISTOR CARBON SMD0805 47R 5% (AC3036)	AC3036
R93	RESISTOR CARBON SMD0805 47R 5% (AC3036)	AC3036
R94	RESISTOR CARBON SMD0805 47R 5% (AC3036)	AC3036
R95	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
R96	RESISTOR METAL FILM SMD0805 10K 1% (AC2841)	AC2841
SW1	SWITCH DPDT WMF LATCHING (AL6824)	AL6824
U1	IC SMD DUAL OP-AMP RC4580 (AE8921)	AE8921
U2	IC SMD DUAL OP-AMP RC4580 (AE8921)	AE8921
U3	IC SMD DUAL OP-AMP RC4580 (AE8921)	AE8921

U4	IC SMD DUAL OP-AMP RC4580 (AE8921)	AE8921
U6	IC SMD DUAL OP-AMP RC4580 (AE8921)	AE8921
U7	IC SMD DUAL OP-AMP RC4580 (AE8921)	AE8921
U9	IC SMD DUAL OP-AMP RC4580 (AE8921)	AE8921
U10	IC SMD DUAL OP-AMP RC4580 (AE8921)	AE8921
U11	IC SMD DUAL OP-AMP RC4580 (AE8921)	AE8921
VR1	POT ALPS 14mm 20KK x2 203K (AI8007)	AI8007